

## RACK SAFETY PLUS, 3 U, 208 / 240 V AC

### FEATURES

19", 3 U Power Distribution Unit with Emergency Stop function

Supplies AC mains power to electrical or electronic devices as a central power switch

208 V phase to phase or phase to neutral or 240 V phase to phase mains input

AC outputs with different connector types, switched by ON/OFF switch

Permanent AC Outputs (Service)

All outputs are protected by circuit breakers

The emergency stop function meets the requirements of EN 60947-5-1 and EN 60204-1 and is vandalism-proof

An additional external emergency stop push button can be connected to the system

### SPECIFICATIONS

Table 1/3

Catalog Number	Product Type	Works With	Socket Type	Rack Height	Function	Input Voltage AC
21272-003	Power Distributor	Varistar, Varistar CP, Novastar	IEC C13 lockable	3 U	Emergency Stop	208 – 240 V
21272-001	Power Distributor	Varistar, Varistar CP, Novastar	IEC C13, IEC C19	3 U	Emergency Stop	208 – 240 V

Table 2/3

Catalog Number	Number of Phases	EMC Filter	Surge Arrester	Inrush Current Limiter	Residual Current Device	Circuit Breaker Cover
21272-003	1	No	No	No	No	No
21272-001	1	Yes	Yes	No	No	No

Table 3/3

Catalog Number	Accessory Type
21272-003	Power distribution accessories

Catalog Number	Accessory Type
21272-001	Power distribution accessories

ADDITIONAL PRODUCT DETAILS

For exact configuration of optional features and example configuration please refer to the item(s) delivered table.

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at [www.nvent.com](http://www.nvent.com) and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.