


SOCKET STRIP, UTE



Modular, compact PDU with many function elements. Using a 1 U by 1 U aluminum chassis the PDU can easily be integrated in a rack with UTE outlets.

CERTIFICATIONS



MERKMALE

230 V, 16 A

In accordance with NFC 61-303

Socket strip with UTE sockets

Mounting height 1 U

Horizontal and vertical mounting

Connecting cable 2 m, with SCHUKO/UTE plug

Socket strips can be rotated through all four directions (in 90° increments) during installation

SPEZIFIKATIONEN

Table 1/2

Katalognummer	Wechselspannung	Product Type	Socket Type	Funktion	Tiefe	Farbe
60110-220	230 V	Socket Strip	UTE		44 mm	Grau
60110-221	230 V	Socket Strip	UTE		44 mm	Grau
60110-222	230 V	Socket Strip	UTE		44 mm	Grau

Katalognummer	Wechselspannung	ProductType	Socket Type	Funktion	Tiefe	Farbe
60110-223	230 V	Socket Strip	UTE		44 mm	Grau
60110-224	230 V	Socket Strip	UTE		44 mm	Grau
60110-225	230 V	Socket Strip	UTE		44 mm	Grau
60110-226	230 V	Socket Strip	UTE		44 mm	Grau
60110-227	230 V	Socket Strip	UTE	Transient Protection	44 mm	Grau
60110-229	230 V	Socket Strip	UTE	Mains Suppression Filter	44 mm	Grau
60110-267	230 V	Socket Strip	UTE	Transient Protection, Mains Suppression Filter	44 mm	Grau
60110-228	230 V	Socket Strip	UTE	Overcurrent Protection	75 mm	Grau
60110-230	230 V	Socket Strip	UTE	Fault Current Protection	88 mm	Grau
60110-231	230 V	Socket Strip	UTE	Fault Current Protection, Overcurrent Protection	88 mm	Grau

Table 2/2

Katalognummer	Länge
60110-220	210 mm
60110-221	438.5 mm
60110-222	947.5 mm
60110-223	1202 mm
60110-224	1753 mm
60110-225	438.5 mm
60110-226	947.5 mm
60110-227	438.5 mm
60110-229	438.5 mm
60110-267	438.5 mm
60110-228	438.5 mm
60110-230	438.5 mm
60110-231	438.5 mm

ADDITIONAL PRODUCT DETAILS

Please order bracket for vertical mounting separately.

WARNUNG

nVent-Produkte müssen in Übereinstimmung mit den Produktinformationsblättern und dem Schulungsmaterial von nVent installiert und verwendet werden. Informationsblätter sind verfügbar unter www.nVent.com sowie bei Ihrem nVent-Kundendienstvertreter. Unsachgemäße Installation, Missbrauch, Fehlanwendung oder andere Handlungen im Widerspruch zu den Anweisungen und Warnungen von nVent können zu Fehlfunktionen, Anlagenschäden, schwerer Körperverletzung sowie zum Tod führen und/oder haben die Annullierung der Garantie zur Folge.



Our powerful portfolio of brands:
nVent.com CADDY ERICO HOFFMAN RAYCHEM SCHROFF
TRACER