

FRONT PANEL, UNSHIELDED, WITH FASTENER PIN



Front panel with GND/earthing connection. The grounding can be done with a cable which fits to the fastener pin on the rear side of the panel.

CERTIFICATIONS



MERKMALE

Enable grounding of the front area (protection class 1)

SPEZIFIKATIONEN

Table 1/3

Katalognummer	Treated Edges	Front Finish	Rear Finish	EMC Shielding	Rack Width	Package Quantity
20119-159	Nein	Anodized	Conductive	Nein	7 HP	1
20119-160	Nein	Anodized	Conductive	Nein	14 HP	1
20119-161	Nein	Anodized	Conductive	Nein	21 HP	1
20119-162	Nein	Anodized	Conductive	Nein	28 HP	1
20119-163	Nein	Anodized	Anodized	Nein	42 HP	1

Table 2/3

Katalognummer	Höhe	Product Type	Typ	Rack Height	Breite	Konform mit
---------------	------	--------------	-----	-------------	--------	-------------

20119-159	128.4 mm	Frontplatte	Front Panel without Handle	3 U	35.2 mm	IEC 60297-3-101, IEEE 1101.1/10
20119-160	128.4 mm	Frontplatte	Front Panel without Handle	3 U	70.8 mm	IEC 60297-3-101, IEEE 1101.1/10
20119-161	128.4 mm	Frontplatte	Front Panel without Handle	3 U	106.3 mm	IEC 60297-3-101, IEEE 1101.1/10
20119-162	128.4 mm	Frontplatte	Front Panel without Handle	3 U	141.9 mm	IEC 60297-3-101, IEEE 1101.1/10
20119-163	128.4 mm	Frontplatte	Front Panel without Handle	3 U	213 mm	IEC 60297-3-101, IEEE 1101.1/10

Table 3/3

Katalognummer	Montage	Material
20119-159	Screw-on Front	Aluminium
20119-160	Screw-on Front	Aluminium
20119-161	Screw-on Front	Aluminium
20119-162	Screw-on Front	Aluminium
20119-163	Screw-on Front	Aluminium

ADDITIONAL PRODUCT DETAILS

Please order fixing material (sleeves, collar screws) separately.

Delivery is in standard pack multiples. Pricing is per individual item.

Please take into consideration that deliveries may be carried out in the stated SPQs (SPQ, e.g. 5 pieces, 10 pieces, 50 pieces, etc.). Differing order quantities (e.g. 2 pieces) may be changed to the next possible delivery quantity = Standard Pack Quantity.

WARNUNG

nVent-Produkte müssen in Übereinstimmung mit den Produktinformationsblättern und dem Schulungsmaterial von nVent installiert und verwendet werden. Informationsblätter sind verfügbar unter www.nVent.com sowie bei Ihrem nVent-Kundendienstvertreter. Unsachgemäße Installation, Missbrauch, Fehlanwendung oder andere Handlungen im Widerspruch zu den Anweisungen und Warnungen von nVent können zu Fehlfunktionen, Anlagenschäden, schwerer Körperverletzung sowie zum Tod führen und/oder haben die Annullierung der Garantie zur Folge.



Our powerful portfolio of brands:
nVent.com CADDY ERICO HOFFMAN RAYCHEM SCHROFF
TRACER