

## SOCKET STRIP, IEC, 3-PHASE



Modular, compact PDU with many function elements. Using a 1 U by 1 U aluminum chassis the PDU can easily be integrated in a rack with IEC C13 and C19 outlets with 3 phase input.

### CERTIFICATIONS



### FEATURES

Socket strips with IEC sockets in accordance with IEC 60320

Vertical mounting

Socket strips can be rotated through all four directions (in 90° increments) during installation

Connecting cable 2 m

Mounting height 1 U

### SPECIFICATIONS

Table 1/2

| Número de catálogo | Tipo de producto | Tipo de toma de corriente | Número de tomas de corriente | Switched Outlets | Color             | Voltaje de CA |
|--------------------|------------------|---------------------------|------------------------------|------------------|-------------------|---------------|
| 60110-283          | Socket Strip     | IEC C13                   | 18                           | No               | Grey, Negro, Rojo | 400V          |
| 60110-284          | Socket Strip     | IEC C13, IEC C19          | 24                           | No               | Grey, Negro, Rojo | 400V          |
| 60110-285          | Socket Strip     | IEC C13, IEC C19          | 30                           | No               | Grey, Negro, Rojo | 400V          |

Table 2/2

| Número de catálogo | Altura | Longitud | Profundidad | Acabado  | Material            | Cantidad de paquetes |
|--------------------|--------|----------|-------------|----------|---------------------|----------------------|
| 60110-283          | 44mm   | 947.5mm  | 44mm        | Anodized | Aluminio, Poliamida | 1                    |
| 60110-284          | 44mm   | 947.5mm  | 44mm        | Anodized | Aluminio, Poliamida | 1                    |
| 60110-285          | 44mm   | 1753mm   | 44mm        | Anodized | Aluminio, Poliamida | 1                    |

## ADDITIONAL PRODUCT DETAILS

Please order bracket for vertical mounting separately.

## ADVERTENCIA

Los productos nVent deben instalarse y usarse solo como se indica en las hojas de instrucciones y materiales de capacitación del producto nVent. Instruction sheets are available at [www.nvent.com](http://www.nvent.com) and from your nVent customer service representative. La instalación incorrecta, el mal uso, la aplicación incorrecta u otras fallas en el seguimiento completo de las instrucciones y advertencias de nVent pueden causar el mal funcionamiento del producto, daños a la propiedad, lesiones corporales graves y la muerte y/o anular la garantía.



Our powerful portfolio of brands:  
**nVent.com CADDY ERICO HOFFMAN RAYCHEM SCHROFF**  
**TRACER**