

ENLOGIC BASIC PDU



The Basic PDU is a cost-effective, reliable power distribution solution. Premium hydraulic-magnetic circuit breakers operate consistently in high-temperature environments. The Basic PDU offers advanced features, such as color-coded locking IEC outlets, a slim chassis design, and toolless mounting backed by a 5-year hassle-free warranty.

CARATTERISTICHE

Black Powder Coated Chassis

IEC 62368 listed. RoHS, and REACH compliant. See drawing for additional information.

SPECIFICHE

Table 1/5

Codice a catalogo	Product Type	Famiglia di prodotti	Switched Outlets	Tipo	Larghezza	Quantità per confezione
EB0860	Socket Strip	Enlogic	No	Basic PDU	56mm	1
EB09JA	Socket Strip	Enlogic	No	Basic PDU	114mm	1

Table 2/5

Codice a catalogo	Tipo di presa	Socket Quantity	Colore	Altezza	Materiale	Finitura
EB0860	(24) C13/C15, (24) C13/C15/C19/C21	48	Black	1490mm	Steel	Powder Coated
EB09JA	(18) C13/C15, (18) C13/C15/C19/C21	36	Black	965mm	Steel	Powder Coated

Table 3/5

Codice a catalogo	Profondità	Tensione nominale	Lunghezza del cavo	Rack Units	Circuit Breaker Quantity	Current Rating
EB0860	55mm	415V	3000m	0U	6	22.1kV·A
EB09JA	75mm	415V	1800m	0U	12	43.5kV·A

Table 4/5

Codice a catalogo	On/Off Switch Included	Number of Output Voltages	Circuit Breaker	Metering Type	Nominal Power Output	Removable Input Cable
EB0860	No		20 A, 1-pole, Hy-MagA	None	230VAC	No
EB09JA	No	36	20 A, 1-pole, Hy-MagA	None	230VAC	No

Table 5/5

Codice a catalogo	Plug Type	Input Cable Length	Output Voltage
EB0860	IEC 60309 530P6/532P6	3m	208 – 230VAC
EB09JA	IEC 60309 560P6/563P6	1.8m	208 – 230VAC

ADDITIONAL PRODUCT DETAILS

Warranty : nVent Enlogic branded equipment provided shall be free from manufacturing defects for a period of five (5) years from the invoice date to the original purchaser.

AVVERTIMENTO

I prodotti nVent devono essere installati e utilizzati solo come indicato nelle schede istruzioni e nei materiali di formazione di nVent. Le schede istruzioni sono disponibili su www.nvent.com e presso il vostro rappresentante del servizio clienti nVent. Un'installazione scorretta, un uso improprio, un'applicazione errata o qualsiasi altro mancato rispetto completo delle istruzioni e degli avvertimenti di nVent può causare malfunzionamenti del prodotto, danni alla proprietà, gravi lesioni personali e morte e/o annullare la vostra garanzia.



Our powerful portfolio of brands:
nVent.com **CADDY ERICO HOFFMAN RAYCHEM SCHROFF**
TRACER