

ENLOGIC BASIC PDU



The Basic PDU is a cost-effective, reliable power distribution solution. Premium hydraulic-magnetic circuit breakers operate consistently in high-temperature environments. The Basic PDU offers advanced features, such as color-coded locking IEC outlets, a slim chassis design, and toolless mounting backed by a 5-year hassle-free warranty.

FEATURES

Black Powder Coated Chassis

IEC 62368 listed. RoHS, and REACH compliant. See drawing for additional information.

SPECIFICATIONS

Table 1/5						
Catalog Number	Product Type	Product Family	Switched Outlets	Туре	Ширина мм	Package Quantity
EB0860	Socket Strip	Enlogic	No	Basic PDU	56mm	1
EB09JA	Socket Strip	Enlogic	No	Basic PDU	114mm	1

Table 2/5						
Catalog Number	Socket Type	Socket Quantity	Color	Высота мм	Material	Finish
EB0860	(24) C13/C15, (24) C13/C15/C19/C 21	48	Black	1490mm	Steel	Powder Coated
ЕВ09ЈА	(18) C13/C15, (18) C13/C15/C19/C 21	36	Black	965mm	Steel	Powder Coated

Table 3/5						
Catalog Number	Глубина мм	Nominal Voltage	Cable Length	Rack Units	Circuit Breaker Quantity	Current Rating
EB0860	55mm	415V	3000m	OU	6	22.1kV·A
EB09JA	75mm	415V	1800m	OU	12	43.5kV·A

Table 4/5						
Catalog Number	On/Off Switch Included	Number of Output Voltages	Circuit Breaker	Metering Type	Nominal Power Output	Removable Input Cable
EB0860	No		20 A, 1-pole, Hy- MagA	None	230VAC	No
EB09JA	No	36	20 A, 1-pole, Hy- MagA	None	230VAC	No

Table 5/5							
Catalog Number	Plug Type	Input Cable Length	Output Voltage				
EB0860	IEC 60309 530P6/532P6	3m	208 - 230VAC				
EB09JA	IEC 60309 560P6/563P6	1.8m	208 - 230VAC				

ADDITIONAL PRODUCT DETAILS

Warranty: nVent Enlogic branded equipment provided shall be free from manufacturing defects for a period of five (5) years from the invoice date to the original purchaser.

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.



Our powerful portfolio of brands: